

Korg M1

MIDI Commander Template Guide



FOR ABLETON MOVE

Korg M1 VST – Filter/Sound Shaping, Amp EG/Modulation, Bank/Program/Mix. CC assignments match Korg M1 V software synthesizer MIDI implementation.

Default MIDI channel: 1.

Device parameters at load

Param	Value
root_note	C
scale	chromatic
layout	fourths
pad_mode	chromatic
drum_base	36
pad_color	cyan
velocity_curve	fixed

Pages overview

Page	Label	Channel
1	Filter/Sound	1
2	Amp EG / Mod	1
3	Bank/Prg/Mix	1

Page details

Page 1 — Filter/Sound

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	Cut	Cutoff	CC 74	default 64
2	Res	Reso	CC 71	default 64
3	EGl	EG Int	CC 79	default 64
4	OSB	OSC Bal	CC 77	default 64
5	FAk	Flt Atk	CC 73	default 64
6	FDc	Flt Dec	CC 75	default 64
7	FRI	Flt Rel	CC 72	default 64
8	IFX	IFX Bal	CC 91	default 64

Page 2 — Amp EG / Mod

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	AAk	Amp Atk	CC 78	default 64
2	ADc	Amp Dec	CC 80	default 64
3	ARI	Amp Rel	CC 83	default 64
4	Mod	ModWhl	CC 1	default 64
5	VDF	VDF MG	CC 2	default 64
6	VDA	VDA MG	CC 92	default 64
7	Exp	Expr	CC 11	default 64
8	Pan	Pan	CC 10	default 64

Page 3 — Bank/Prg/Mix

Channel 1.

Encoder	Label	Full Name	Output	Notes
1	BMS	BnkMSB	CC 0	

Encoder	Label	Full Name	Output	Notes
2	BLS	BnkLSB	CC 32	
3	Prg	Program	Program Change	
4	Vol	Volume	CC 7	
5	IFX	IFX Bal	CC 91	
6	Rot	Rotary	CC 76	
7	---		CC 255	
8	---		CC 255	

Generated from `presets/library/korg-m1.json`. Regenerate via `python3 tools/generate_template_docs.py`.